

AG-2-GSB-MA26XX

----- Pre-calibrated module Instruction Manual

NOVEMBER 6, 2024

Contents

| | |
|---|----------|
| Product Description | 3 |
| Technical Specification | 3 |
| Product Appearance and Dimensions..... | 4 |
| Pin Configuration | 4 |
| Communication Protocol and Description | 5 |
| Application Notes | 5 |

Product Description

The AG-2-GSB-M26XX is an embedded type module equipped with the Figaro's TGS26 series semiconductor Sensor, capable of detecting via gases such as methane (CH₄), LP gas, and Hydrogen (H₂) in diverse environments. The module has been pre-calibrated before leaving the factory and has good durability, stability, and anti-poisoning. It includes a built-in temperature sensor for data correction via software algorithms to minimize environmental impact on measurement accuracy. It utilizes digital communication through a UART bus output for gas concentration readings, which allows users to easily and quickly integrate the module into various systems. This makes it suitable for both residential and industrial gas detection applications.

Technical Specification

| Item | Specification |
|---------------------|---|
| Model Number | AG-2-GSB-M26XX |
| Target Gases | CH ₄ , C ₃ H ₈ , H ₂ etc. |
| Sensing Principle | Semiconductor |
| Detection Range | See corresponding sensor spec |
| Resolution | See corresponding sensor spec |
| Measurement Error | < ±5% FS |
| Operating Voltage | 5V±0.1V DC |
| Operating Current | See corresponding sensor spec |
| Output Signal | UART (+3.3V TTL) |
| Temperature Range | -10 - 55°C |
| Humidity Range | 0% -90%RH |
| Pressure Range | 1 ± 0.1 atm |
| Storage Temperature | 10 - 40°C |
| Size | L*W*H=41mm*27mm*22mm (TGS2610-D) |
| Expected Life | See the corresponding sensor data sheet for details. |

Product Appearance and Dimensions



Pin Configuration

The module reserves a 3P + 4P pin header with a pitch of 2.54 mm as the electrical interface. Pin descriptions are as follows:

| Pin Number | Name | Functional Description |
|------------|------|---|
| 1 | VIN | Power supply, 5V DC |
| 2 | GND | Signal ground |
| 3 | RXD | Serial port input, Connected to the host TXD |
| 4 | TXD | Serial port output, Connected to the host RXD |
| 5 | VOT | Module onboard 3.3V reference power output (maximum output capacity 50mA) |
| 6 | FAT | Fault signal output pin (reserved) |
| 7 | ALM | Alarm signal output pin (reserved) |

Note:

- 1) After being powered-on, the module needs approximate 4 minutes to warm up. Once the process is complete, the module enters into normal monitoring state.
- 2) After being powered-on, the module's serial port outputs a frame of data containing status and concentration values every 1 second.

Communication Protocol and Description

1. Serial communication adopts module active upload data mode, data upload interval 1 second.
2. UART serial port:
Baud rate: 4800, data bits: 8bit, stop bits: 1bits, parity bit: no parity

3. The data frame is 5 bytes and has the following data format:

| Frame Header | Status | Conc. high byte | Conc. low byte | Checksum |
|--------------|--------|-----------------|----------------|----------|
| 0xAA | State | D(H) | D(L) | Sum |

Checksum Sum = 0xAA + State + D(H) + D(L)

The module state byte is defined as follows:

| Operating properly | Module Circuit Fault | Power On to Warm Up |
|--------------------|----------------------|---------------------|
| 0x80 | 0x81 | 0x82 |

Note: Concentration values are all 0 during the module warm-up period; When the concentration value is 0xffff, it indicates an over-range condition.

Example:

Module upload: 0xAA 0x80 0x00 0x0A 34

Indicates that the module is in normal monitoring state and the current gas concentration is 10%LEL.

4. The above communication protocols are only for module testing, and can also be customized according to customer requirements.

Application Notes

1. The module is not protected against reverse polarity or ESD (Electrostatic Discharge). Users should ensure correct power connection and implement appropriate ESD protection measures when using the module.
2. Exceeding the module power supply voltage range may cause damage to the module or the module may fail to operate properly.
3. Please follow precautions specific to the sensor when using the module.