# Sweek.com

# **BDS Series Pressure Sensor**



#### **Features**

- Dual Sensing Elements (Absolute & Differential)
- Top constraint absolute sensing element for helium applications
- Parylene coating available upon request
- RoHS Compliant

#### Applications

• Gas Flow Measurement

## **General Description**


The BDS Basic Pressure Sensor was designed with the idea of combining two sensing elements into one package. This sensor is designed to provide a precise flow measurement by combining a differential and absolute sensing element in the same package. By combining the differential and absolute sensing element, engineers can save cost and space in today's smaller devices.

The BASIC series pressure sensors are based upon a proprietary technology to reduce the size of the sensor and yet maintain a high level of performance. Output offset errors due to position sensitivity; packaging stress and long term drift are all significantly reduced when compared to conventional silicon sensors. In addition, the sensor utilizes a silicon, micromachined, stress concentration enhanced structure to provide a very linear output to measured pressure.

This series is intended for use with non-corrosive, non-ionic working fluids such as air, dry gases and the like.

The output of the device is ratiometric to the supply voltage.

#### **Physical Dimensions**




iSweek www.isweek.com

 Add: 16/F, Bldg. #3, Zhongke Mansion, No.1 Hi-Tech S. Rd, Hi-Tech Park South, Shenzhen, Guangdong, 518067 P.R.China

 Tel: + 86-755-83289036
 Fax: + 86-755-83289052

 E-mail: sales@isweek.com

# Sweek.com



#### **Standard Pressure Range**

			<u>S</u>	ensitivity (1)		
Device Type	<b>Operating Pressure</b>	Nominal	Std Dev.	Units	<b>Proof Pressure</b>	Burst Pressure
BDS-L10D030A						
Absolute	0 - 30 PSIA	7.5	±1.25	mV/PSI	90 PSI	150 PSI
Differential	0 - 10 inH2O	3.0	±0.40	mV/inH2O	15 PSI	30 PSI
BDS-L10D100A						
Absolute	0 - 100 PSIA	3.0	±0.28	mV/PSI	150 PSI	150 PSI
Differential	0 - 10 inH2O	3.0	±0.40	mV/inH2O	15 PSI	30 PSI

#### Performance Characteristic: BDS-L10D030A Absolute Element

Parameter <sup>(1)</sup>	Minimum	Nominal	Maximum	Units	
Offset Voltage (@1 atm)	+25		+125	mv	
Temperature Effect on Offset (2)		±3		uV/V/°C	
Temperature Effect on Resistance (2,5)	1700	2600	3100	ppm/°C	
Temperature Effect on Span (2,5)	-1500	-1900	-2400	ppm/°C	
Linearity error <sup>(4,5)</sup>		±0.2	±0.5	% FSS	
Hysteresis error		±0.01		% FSS	
Input Resistance	2.0	2.5	3.0	kohms	
Output Resistance	2.0	2.5	3.0	kohms	
Long term stability <sup>(3)</sup>		0.1		% FSS	

Sweek www.isweek.com

 Add: 16/F, Bldg. #3, Zhongke Mansion, No.1 Hi-Tech S. Rd, Hi-Tech Park South, Shenzhen, Guangdong, 518067 P.R.China

 Tel: + 86-755-83289036
 Fax: + 86-755-83289052

 E-mail: sales@isweek.com

Differential Element	Minimum	Manalasi	Maximum	11.11
Parameter <sup>(1)</sup>	Minimum	Nominal	Maximum	Units
Offset Voltage		±5.0	±25.0	mv
Temperature Effect on Offset (2)		±3.0		uV/V/°C
Temperature Effect on Resistance (2,5)	2300	2600	3300	ppm/°C
Temperature Effect on Span (2,5)	-1700	-2200	-2700	ppm/°C
Linearity error (4,5)		±0.5	1.0	% FSS
Hysteresis error		±0.01		% FSS
Position Sensitivity (5)		±0.01	±0.03	% FSS
Warm Up Shift		±10.0		uV
Input Resistance	1.3	1.6	2.5	kohms
Output Resistance	1.3	1.6	2.5	kohms
Long term stability (3)		0.1		% FSS

## Performance Characteristic: BDS-L10D100A

Absolute Element Parameter <sup>(1)</sup>	Minimum	Nominal	Maximum	Units	
Offset Voltage (@1 atm)	-20.0		+120	mv	
Temperature Effect on Offset <sup>(2)</sup>		±3.0		uV/V/°C	
Temperature Effect on Resistance (2,5)	1200	2600	3100	ppm/°C	
Temperature Effect on Span <sup>(2,5)</sup>	-1500	-1900	-2400	ppm/°C	
Linearity error (4,5)		±0.2	±0.5	% FSS	
Hysteresis error		±0.01		% FSS	
Input Resistance	2.0	2.5	3.0	kohms	
Output Resistance	2.0	2.5	3.0	kohms	
Long term stability <sup>(3)</sup>		0.1		% FSS	

## **Differential Element**

Parameter <sup>(1)</sup>	Minimum	Nominal	Maximum	Units	
Offset Voltage		±5.0	±25.0	mv	
Temperature Effect on Offset <sup>(2)</sup>		±3.0		uV/V/°C	
Temperature Effect on Resistance (2,5)	2300	2600	3300	ppm/°C	
Temperature Effect on Span <sup>(2,5)</sup>	-1700	-2200	-2700	ppm/°C	
Linearity error <sup>(4,5)</sup>		±0.5	±1.0	% FSS	
Hysteresis error		±0.01		% FSS	
Position Sensitivity <sup>(5)</sup>		±0.01	±0.03	% FSS	
Warm Up Shift		±10		uV	
Input Resistance	1.3	1.6	2.5	kohms	
Output Resistance	1.3	1.6	2.5	kohms	
Long term stability <sup>(3)</sup>		0.1		% FSS	

iSweek www.isweek.com

 Add: 16/F, Bldg. #3, Zhongke Mansion, No.1 Hi-Tech S. Rd, Hi-Tech Park South, Shenzhen, Guangdong, 518067 P.R.China

 Tel: + 86-755-83289036
 Fax: + 86-755-83289052

 E-mail: sales@isweek.com

#### **Ordering Information**

0			
Part Number	Configuration		
	Differential	Absolute	
	Sensor	<u>Sensor</u>	Package
BDS-L10D030A-N9	10 inH2O	30 PSIA	N9
BDS-L10D100A-N9	10 inH2O	100 PSIA	N9

#### Specification Notes

NOTE 1: ALL PARAMETERS ARE MEASURED AT 5.0 VOLT EXCITATION, FOR THE NOMINAL FULL SCALE PRESSURE AND ROOM TEMPERATURE UNLESS OTHERWISE SPECIFIED. PRESSURE MEASURE-MENTS ARE WITH POSITIVE PRESSURE TO PORT B.

NOTE 2: SHIFT IS RELATIVE TO 25°C.

NOTE 3: SHIFT IS WITHIN THE FIRST YEAR OF OPERATION.

NOTE 4: MEASURED AT ONE-HALF FULL SCALE RATED PRESSURE USING BEST STRAIGHT LINE CURVE FIT.

NOTE 5: PARAMETER IS CHARACTERIZED AND NOT 100% TESTED. MINIMUM AND MAXIMUM VALUES INDICATED AS A DESIGN REFERENCE.

All Sensors reserves the right to make changes to any products herein. All Sensors does not assume any liability arising out of the application or use of any product or circuit described herein, neither does it convey any license under its patent rights nor the rights of others.